# Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



# APC Smart-UPS SRT 48V 1kVA 1.5kVA RM Battery Pack



SRT48RMBP

### Overview

Lead time Usually in Stock

### Main

Product or component type	Battery	
Number of rack unit	2U	
Battery type	Lead-acid battery	
Provided equipment	Documentation CD Installation guide Rack mounting brackets Warranty card	
Range of product	Smart-UPS Battery Systems	

### **Batteries & Runtime**

Number of battery free slots	0
Number of battery filled slots	0
Device mounting	Stand alone battery stack
Battery voltage	48 V
Number of battery replacement quantity	2
Replacement battery	APCRBC155 □

# **Physical**

Colour	Black
Height	8.5 cm
width	43.2 cm
Depth	53.6 cm
Net weight	29.9 kg
Mounting mode	Rack-mounted

### **Environmental**

Ambient air temperature for operation	040 °C	
Operating altitude	010000 ft	
Relative humidity	095 % non-condensing	
Ambient air temperature for storage	-1545 °C	

Storage altitude	0.000000000015240.0000000000 m
Storage Relative Humidity	095 % non-condensing

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	24.5 cm
Package 1 Width	69.0 cm
Package 1 Length	59.5 cm
Package 1 Weight	32.58 kg

# **Contractual warranty**

Warranty 2 years repair or replace

# **Environmental Data**

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

How this information helps you  $\geq$ 

⊘ Environmental footprint	
Environmental Disclosure	Product Environmental Profile

### **Use Better**

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
SCIP Number	409c68a1-39a6-4e5f- b080-12befe783ad8
REACh Regulation	REACh Declaration
☼ Energy efficiency	
Optimized Energy Efficiency	Energy efficient product

# **Use Again**

Control Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable

Take-back

Yes

Image of product / Alternate images

**Alternative** 



